



## LS

## Recessed

2,4W / 65lm / 5000K / 325x235x60mm

15903

Desing: Eduardo Souto de Moura

Emergency recessed luminaire with body made of aluminium profile with matt finish or electrostatic 100% polyester paint with textured-finish.

Pictogram, with acrylic structure and adhesive film, supplied separately.

The same luminaire allows maintained or nonmaintained mode.

Luminaire with self-testing mode.

Prepared for remote control (rest mode).

3-hour autonomy.

Compliant with the following standards:

EN60598-2-22 / EN60598-1 / UNE 20392

Power supply included. IP22 | 230Vac | 50/60Hz





mm

5000K	Light Source	Luminaire
Power	2,4W	3,1W
Flux	340lm	65lm
Efficiency	142lm/W	21lm/W
LOR	-	19%
UGR	-	-

135°	150°	165°	180°	1650	150°	135°	Beam angle
			160				-
120°			120			1200	
			80	$/ \ge$			
105*	A				1	1050	Application
900			$\mathcal{L}$			900	
~			£.			)	
750	1	$\sim$		X		750	Maight
	$\times$	$\times /$			$\rightarrow$		Weight
60°		->-		1	$\times$	60°	1,5Kg
						. /	
						$\times$ L	
45°	30°	150	0.0	15°	30°	45°	


## **Rest Mode features**

## Rest Mode / Inhibit Mode

Emergency operation is automatically started when the mains supply is switched off. If the Rest Mode is activated, the discharging of the battery will be minimized by switching off the LED output. If the inhibit Mode has been activated before the mains supply is switched off, Rest Mode will be automatically activated if the mains supply is switched off within 15 minutes. Rest Mode and Inhibit Mode can be initiated by applying a short pulse between 9.5 and 22.5 V in amplitude for a period of 150 to 1000 ms. This pulse shall be applied to terminals marked Rest.

After a mains reset the EM powerLED ST exists the Rest Mode. Rest Mode and Inhibit Mode can both be disabled by applying a voltage pulse of 1000 to 2000 ms to the terminals marked as Rest to send the RE-LIGHT/ RESET INHIBIT command.

Pulse/Mode	Standby	Emergency	Rest
150 - 1,000 ms	Inhibit	Rest	-
1,000 - 2,000 ms	Cancel inhibit	-	Re-light



∠Z 327x65

