

41W / 3510lm / 3000K / DALI / Diffuse /  
1679mm

61957

Design: O/M  
LED light source with good colour consistency and  
long operation lifespan.

LED CRI>80 / >50.000h, L80/B10 / 3-step MacAdam  
Power supply included.  
IP20 | 230Vac | 50/60Hz



- Structure**
  - 1 Profile
  - 2 End caps
  - 3 Fitting accessories
  - 4 Profile coupling
- Diffuser**
  - A Polycarbonate frost diffuser
- Light Source**
  - B LED Modules

LED	3000K	Light Source	Luminaire
Power		41W	48,2W
Flux		7350lm	3510lm
Efficiency		179lm/W	73lm/W
LOR		-	48%
UGR		-	<25



Beam angle  
Diffuse

Application



Weight  
0,6Kg



Finishes

For the specific supply of "DALI 2" drivers, please contact:  
[support@om-light.com](mailto:support@om-light.com)

Choose the length and layout of the system exactly as you want it, to  
model the right lighting functions for different tasks. For further  
information please contact: [support@om-light.com](mailto:support@om-light.com)

Data according to regulations  
2019/2020/EU supplemented by 2021/341 | 2019/2015/EU  
supplemented by 2021/340/EU Energy Consumption Labelling  
Ordinance. This product contains light sources of efficiency class C  
Model Identifier 89603216

